



## Chain Conversion

### TYPE

SC = semi-chisel

C = chisel

R = ripping

### STYLE

RK = reduced kickback

S = standard

H = harvester

### SEQUENCE

SKIP = skip sequence

All others standard

Chart is sorted by pitch

TYPE	STYLE	PITCH	GAUGE	CARLTON	SILVERSTREAK	GB	OREGON	STIHL	SABRE	WINDSOR
SC	RK	3/8 LP	0.043	N4C-BL/095-210	095-2107	R43S-1S/095-210	90SG	61PMMC3	357NKD	43RG
SC	S	3/8 LP	0.043	N4C	094-2007	R43S-1P	90SG	61PMN	357NKD	43RG
SC	RK	3/8 LP	0.05	N1C-BL/095-310	095-3107	R50S-1S	91VG/91PX	63PMC3/63PM1	357D	50RG
SC	S	3/8 LP	0.05	N1C/094-310	094-3107	R50S-1P	91VX/91VXL	63PM	357	50R
SC	RK	0.325	0.05	K1C-BL/097-310	097-3107	J50S-1S	33SL	23RM2	520D	50JG
SC	S	0.325	0.05	K1C /096-310	096-3107	J50S-1P	20BPX	23RMC	520	50J
SC	RK	0.325	0.058	K2C-BL/097-410	097-4107	J58S-1S	34SL	25RM2	528D	58JG
SC	S	0.325	0.058	K2C/096-410	096-4107	J58S-1P	21BPX	25RMC	528	58J
SC	RK	0.325	0.063	K3C-BL/097-510	097-5107	J63S-1S	35SL	26RM2	523D	63JG
SC	S	0.325	0.063	K3C/096-510	096-5107	J63S-1P	22BPX	26RMC	523	63J
C	RK	0.325	0.05	K1L-BL	099-3107	J50C-1S	33SL	23RMC3	920D	50JLG
C	S	0.325	0.05	K1L/098-310	098-3107	J50C-1P	20LPX	23RS	920	50JL
C	RK	0.325	0.058	K2L-BL	099-4107	J58C-1S	34SL	25RMC3	928D	58JLG
C	S	0.325	0.058	K2L/098-410	098-4107	J58C-1P	21LPX	25RS	928	58JL
C	RK	0.325	0.063	K3L-BL/099-510	099-5107	J63C-1S	35SL	26RMC3	923D	63JLG
C	S	0.325	0.063	K3L/098-510	098-5107	J63C-1P	22LPX	26RS	923	63JL
SC	RK	3/8	0.05	A1EP-GL/091-310	091-3107	A50S-1S	72V	33RSC3	880D	50AG
SC	S	3/8	0.05	A1EP/090-310	090-3107	A50S-1P	72DG/72DG	33RM	880	50A
SC	S	3/8	0.058	A2EP/090-410	090-4107	A58S-1P	73DG/73DP	35RM 1	888	58A/58AG
SC	S	3/8	0.063	A3EP/090-525	090-5257	A63S-1P	75DG/75DP	36RM/36RM1	883	63A/63AG
C	RK	3/8	0.05	A1LM-GL	093-3257	A50C-1S	72V	33RM2	980D	
C	S	3/8	0.05	A1LM/092-310	092-3107	A50C-1P	72LGX	33RS/33RSC	980	50APL
C	S	3/8	0.058	A2LM/092-410	092-4107	A58C-1P	73LGX	35RS	988	58APL
C	S	3/8	0.063	A3LM/092-800		A63C-1P	75LGX	36RS/36RSC	983	63APL
R	S	3/8	0.058	A2EP-RP/092-725		A58R-1P/086-042	73RD		888R	
SC	S	0.404	0.058	B2EP/089-425	089-4287	B58S-1P	58AC	45RM	J58	58B
SC	S	0.404	0.063	B3EP/089-300		B63S-1P	27	46RM	J63	63B
SC	H	0.404	0.063	B3M		B63SH-1P/087-034	16H	46RHM	MK	HC
C	S	0.404	0.063	B3LM/089-400		B63C-1P/086-049	59L	46RS	923	63BL
Chipper	H	3/4	0.122	G7S		C122PH-1P/087-001	11BC			3HC